CONNECTORS AND ADAPTERS

SN shuttered adapter, SC footprint

Shuttered SN adapter in the SC footprint, 2-channel or 4-channel, with internal shutters on every port.

KEY FEATURES

- SC footprint, drops into SC cut-outs
- 2-channel (4 fibre) or 4-channel (8 fibre)
- Internal shutters on each port
- Typical insertion loss 0.10 dB
- Rated for 200 matings per GR-326-Core

SPECIFICATIONS

Type	SN adapter, shuttered
Footprint	SC
Channels	2-channel (4 fibre) or 4-channel (8 fibre)
Shutter	Internal shutters
Typical insertion loss	0.10 dB
Maximum insertion loss	0.20 dB
Operating temperature	-40 to +75 C
Humidity resistance	95 percent
Durability	200 matings per GR-326-Core
Sleeve	Precision zirconia

APPLICATIONS

- Patch panels and cassettes using SN ports
- Dense data centre racks
- 400G links on SN connectors

HOW TO ORDER, SEND US

- Channel count and shuttered or non-shuttered
- Footprint or cut-out the adapter must fit
- Connector type that will plug in each side
- Quantity of adapters
- Panel or cassette drawing, if you have one



OPTIONS

Channels	2-channel (4 fibre), 4-channel (8 fibre)

Price on request

Send your drawing or part list. An engineer reads every request and replies with questions or a quote.

Request a quote

Scan, or open radixfibrotech.com/connectors/sn-shuttered-adapters-sc-footprint/

Specifications are as published for this product. The final specification, lengths and lead time are confirmed in your quotation.